

Converging Innovations, Expanding Solutions







SPRING CLAMP (SCREWLESS) TERMINALS (SOLUTIONS FOR RAILWAYS)



Converging Innovations, Expanding Solutions



SPRING CLAMP (SCREWLESS) TERMINALS (SOLUTIONS FOR RAILWAYS)



SERVING TO INDIAN RAILWAYS
















Index

∏ie

Page

Sr. No. FAQs : Spring Clamp (Screwless) Termination

Elmex Spring Clamp (Screwless) Terminals : Overview

Elmex Range of Spring Clamp (Screwless) Terminals

Elmex Valued Customers



FAQs: SPRING CLAMP (SCREWLESS) TERMINATION

What is the basic difference in termination of screw clamp connection and spring clamp connection?


In case of screw clamp connections, it is necessary to ensure proper tightening of screw with a torque screwdriver. This is possible under controlled conditions like factory wiring where personnel with skill and torque screwdrivers are readily available but the same may not be the case for field wiring applications. In screwless terminal blocks spring clamp is opened by insertion of a screwdriver. Conductor is inserted into this 'opened' clamp and connection is secured as some as the screwdriver is withdrawn.

How does screwless termination improve wiring efficiency?

The wiring time for making screwless connection is significantly less than that required for making screw clamp connection particularly because operation of opening the screw and tightening it after insertion of conductor is eliminated while making spring clamp connections.

How damage to conductor is prevented in spring clamp connection?

The clamping force in spring clamp connection



adjusts automatically according to cross-section of the conductor inserted. Larger the conductor, more the force exerted on it. There are no external factors which can change this force. This is practically not so for other termination technologies and there are chances of damage to conductor if excessive tightening torque is applied. In spring clamp connection it is the flat face of the spring clamp which presses the conductor against current bar, at a force which is governed by spring clamp design itself.

How is spring-clamp connection corrosion resistant?

This is because of two reasons. Firstly, the spring clamp material is special grade stainless steel which has excellent resistance to corrosion. Secondly, spring clamp connection is a "gas-tight" connection, which prevents entry of corrosive gases to termination contact area.

Can two conductors be inserted into single spring clamp?

This is not a recommended practice as two wires inserted in one single clamping unit will not allow application of uniform contact pressure by the spring clamp.



elmex' SPRING CLAMP TERMINALS: OVERVIEW

conductor within the clamping unit good engineering practices. As the name suggests, these terminal blocks do not require a screw for termination of a 'elimex' Screwless Terminal Blocks are constructed employing

performance of Screwless Terminal Blocks are described as under: Some of the salient features with respect to construction and

- material which is heat treated for stress relieving at our end. Important characteristics of this spring steel material are as are made using special grade Austenitic Stainless Steel 1) The Spring Clamp used in 'elimex' Screwless Terminal Blocks
- High fatigue strength
- Better resistance to corrosion effects
- temperatures Higher relaxation resistance, especially at elevated
- ultimate tensile strength High ductility, low yield stress and relatively high





conductor entry i.e. side entry, top entry and angular entry to choose from depending on termination requirement These terminal blocks are available with multiple options for









of spring clamp termination is secured with spring action force after inserting with a screw driver which is to be withdrawn a conductor is inserted after opening the clamp up screws and tighten them up after conductor type terminal blocks, it is required to open wiring efficiency and speed. In screw clamp insertion. In screwless type terminal blocks, a These terminals the conductor and the increase

short two terminals with one shorting link construction of the terminal block. Thus we can these terminal blocks have provision to accept links, in required numbers. Current bars in by using just two way push in type shorting three terminals with two shorting links, and two shorting links, which can be inserted 4) These terminals can be interconnected top or side depending upon



- applying the specified torque as it required to be done for the other or a stud and nut mechanism, there is no question of setting and types of terminal blocks. Since the termination is by spring force action and without a screw 5) Torque application for termination is not required:
- if not done carefully can result in unreliable joint. These terminals a ring or fork type lug by additional operation of crimping which can securely clamp conductors crimped with pin type lugs also. and insert it into the clamp i.e. no need to prepare conductor with one just needs to strip the conductor for the specified stripping length are so designed that thay do not require conductor preparation i.e. Ease of using unprepared conductors: These terminal blocks
- to 4 sq mm. To facilitate mounting on the surface, these terminal fixed through these mounting holes. insulation housing. On the other side, it is provided on the end plate. blocks are provided with mounting facility (hole) on one side of the mount models are also available for termination of conductor size up standard DIN rail type TS 35 / IEC Top Hat rail TH 35. Surface 7) In general, these terminal blocks are designed for mounting on The screws for fixing the stack of terminal blocks on the surface are





elmex' RANGE OF SPRING CLAMP (SCREWLESS) TERMINAL BLOCKS

FEED THROUGH TERMINAL BLOCKS: TOP ENTRY

DST 4

(@ @















DST 16

(A)








SCT 2.5



















IEC 60947-7-1: 800 V/41 A/6 sq mm

IEC 60947-7-1: 800 V/57 A/10 sq mm





MULTIPLE OUTPUT TERMINAL BLOCKS

DCT 2.5 - 1x2

(**919 91**

DCT 2.5 - 2x2 ((91) . 91 (8)

DST 2.5 - 1x2

3

DST 2.5 - 2x2

3





IEC 60947-7-1: 800 V/24 A/2.5 sq mm FU FU : 600 V/15 A/14-22 AWG

IEC 60947-7-1: 800 V/24 A/2.5 sq mm FN FN : 600 V/15 A/14-22 AWG
















IEC 60947-7-1: 800 V/24 A/2.5 sq mm IEC 60947-7-1: 1000 V/17.5 A/2.5 sq mm



elmex'RANGE OF SPRING CLAMP (SCREWLESS) TERMINAL BLOCKS

MULTIPLE OUTPUT TERMINAL BLOCKS DSDD 2.5 IEC 60947-7-1: 800 V/24 A/2.5 sq mm 2 IEC 60947-7-1: 500 V/20 A/2.5 sq mm DS3L 2.5 2 IEC 60947-7-1: 250 V/10 A/1.5 sq mm DS8L P16 2 IEC 60947-7-1: 250 V/10 A/1.5 sq mm DS8L P32 2









'elmex' RANGE OF SPRING CLAMP (SCREWLESS) TERMINAL BLOCKS

DISCONNECT TERMINAL BLOCKS







DSDT 2.5WOSL













IEC 60947-7-1: 800 V/24 A/2.5 sq mm : 600 V/15 A/14-20 AWG

IEC 60947-7-1: 1000 V/17.5 A/2.5 sq mm

IEC 60947-7-1: 1000 V/17.5 A/2.5 sq mm

IEC 60947-7-1: 400 V/10 A/2.5 sq mm

IEC 60947-7-1: 400 V/41 A/6 sq mm

PANEL MOUNTED TERMINAL BLOCKS

MCT 1.5

2

MCT 2.5 ((91) . 91 (1)

MCT 2.5P4 ((711 .711 &

MCT 4

(C) (M) (D)



IEC 60947-7-1: 500 V/17.5 A/1.5 sq mm FRONT VIEW SIDE VIEW



IEC 60947-7-1: 500 V/24 A/2.5 sq mm .91.91 : 300 V/15 A/14-22 AWG

IEC 60947-7-1: 500 V/24 A/2.5 sq mm SU SU : 300 V/15 A/14-22 AWG

FRONT VIEW SIDE VIEW

SCREWLESS SIDE CLAMPS

SCUSL

FRONT VIEW SIDE VIEW





















-20 AWG	/4 sq mm
Ī	<u></u>
(9)	C 60947-7
: 300 V/20	1: 500 V/32 A/4 st
: 300 V/20 A/12-20 AWG	/32 A/4 sq mi
WG	mm

IEC 60947-7-1: 500 V/32 A

: 300 V/20 A/12

FRONT VIEW

SIDE VIEW

FRONT VIEW

SIDE VIEW







PLUG AND SOCKET TERMINALS

DPSC 5.08











IEC 60947-7-1: 800 V/24 A/2.5 sq mm


IEC 60947-7-1 : Male : 250 V/16 A/2.5 sq mm Female : 250 V/16 A/2.5 sq mm

IEC 60947-7-1 : Male : 400 V/16 A/2.5 sq mm Female : 400 V/16 A/2.5 sq mm



















Rockwell Automation





SIEMENS

BOMBARDIER







Honeywell













Converging Innovations, Expanding Solutions



Solutions For Metering & Protection

Solutions For Solar Photovoltaic



Solutions For Oil & Gas Industry















Elmex Controls Pvt. Ltd. Elmex Electric Pvt. Ltd.

12, GIDC Estate, Makarpura Road, Vadodara 390010, Gujarat, India

(**E) +91-265 2642021, 2642023

(**E) marketing@elmex.net (**E) www.elmex.net









